

## 37 Series Marker Lamps

- Easy to fit - No tools required
- Serrated plug and 3M tape
- 5 Year warranty



### Part Number

- 37RM2P** - Multivolt 12-24V, Blister Single
- 37RMB2P** - Multivolt 12-24V, Bulk poly bag
- 37RMB3** - Multivolt 12-24V, 3m Cable, Bulk poly bag

**Function** Rear end outline marker  
**Size** 70mm x 35mm x 20mm  
**Voltage** Multivolt 12-24V  
**LED Qty** 2  
**Cable** 10cm with specially designed plugs or 3 meter cable

**Draw** @13.8V @28V  
 0.04A 0.04A

**Approvals** **Function** **Category** **CRN**  
**ECE** Rear end 02R1 6917



### Part Number

- 37AM2P** - Multivolt 12-24V, Blister Single
- 37AMB2P** - Multivolt 12-24V, Bulk poly bag
- 37AMB3** - Multivolt 12-24V, 3m Cable, Bulk poly bag

**Function** Side marker  
**Size** 70mm x 35mm x 20mm  
**Voltage** Multivolt 12-24V  
**LED Qty** 2  
**Cable** 10cm with specially designed plugs or 3 meter cable

**Draw** @13.8V @28V  
 0.04A 0.04A

**Approvals** **Function** **Category** **CRN**  
**ECE** Marker 00SM1 1017



### Part Number

- 37ARM2P** - Multivolt 12-24V, Blister Single
- 37ARMB2P** - Multivolt 12-24V, Bulk poly bag
- 37ARM3** - Multivolt 12-24V, 3m Cable, Bulk poly bag

**Function** Side marker  
**Size** 70mm x 35mm x 20mm  
**Voltage** Multivolt 12-24V  
**LED Qty** 2  
**Cable** 10cm with specially designed plugs or 3 meter cable

**Draw** @13.8V @28V  
 0.04A 0.04A

**Approvals** **Function** **Category** **CRN**  
**ADR** Side 45/01 43515



### Part Number

- 37WM2P** - Multivolt 12-24V, Blister Single
- 37WMB2P** - Multivolt 12-24V, Bulk poly bag
- 37WM3** - Multivolt 12-24V, 3m Cable, Bulk poly bag

**Function** Front end outline marker  
**Size** 70mm x 35mm x 20mm  
**Voltage** Multivolt 12-24V  
**LED Qty** 2  
**Cable** 10cm with specially designed plugs or 3 meter cable

**Draw** @13.8V @28V  
 0.04A 0.04A


**Approvals** **Function** **Category** **CRN**  
**ECE** Front 02A 6918

### Fitting Instructions

Drill two 6mm holes for serrated plugs and one 8mm hole or larger for the cable. Remove the 3M protective film from the back of the lamp and simply push into place. Please refer to ADR 13/00 for mounting instructions.



### Technical Drawings



### Blister Packaging



## Chrome Surround Coloured Lens Marker Lamps

- Easiest to fit - No tools required
- Serrated plug and 3M tape
- 5 Year warranty



### Part Number

**37CRM2P** - Multivolt 12-24V, Blister Single  
**37CRMB2P** - Multivolt 12-24V, Bulk boxed

**Function** Rear end outline marker  
**Size** 70mm x 35mm x 20mm  
**Voltage** Multivolt 12-24V  
**LED Qty** 2  
**Cable** 10cm with specially designed plugs

**Draw** @13.8V @28V  
 0.04A 0.04A

**Approvals** **Function** **Category** **CRN**  
**ECE** Rear end 02R1 6917



### Part Number

**37CAM2P** - Multivolt 12-24V, Blister Single  
**37CAMB2P** - Multivolt 12-24V, Bulk boxed

**Function** Side direction indicator  
**Size** 70mm x 35mm x 20mm  
**Voltage** Multivolt 12-24V  
**LED Qty** 2  
**Cable** 10cm with specially designed plugs

**Compliance** ECE 00SM1 - CRN 1017

**Draw** @13.8V @28V  
 0.04A 0.04A

**Approvals** **Function** **Category** **CRN**  
**ECE** Indicator 00SM1 1017



### Part Number

**37CARM2P** - Multivolt 12-24V, Blister Single  
**37CARMB2P** - Multivolt 12-24V, Bulk boxed

**Function** Side marker  
**Size** 70mm x 35mm x 20mm  
**Voltage** Multivolt 12-24V  
**LED Qty** 2  
**Cable** 10cm with specially designed plugs

**Draw** @13.8V @28V  
 0.04A 0.04A

**Approvals** **Function** **Category** **CRN**  
**ADR** Side 45/01 43515



### Part Number

**37CWM2P** - Multivolt 12-24V, Blister Single  
**37CWMB2P** - Multivolt 12-24V, Bulk boxed

**Function** Front end outline marker  
**Size** 70mm x 35mm x 20mm  
**Voltage** Multivolt 12-24V  
**LED Qty** 2  
**Cable** 10cm with specially designed plugs


**Draw** @13.8V @28V  
 0.04A 0.04A

**Approvals** **Function** **Category** **CRN**  
**ECE** Front 02A 6918

## Fitting Instructions

Drill two 6mm holes for serrated plugs and one 8mm hole or larger for the cable. Remove the protective film from the back and simply push into place. Please refer to ADR 13/00 for mounting instructions.

## Technical Drawings



## Blister Packaging



**Clear lens  
Coloured LEDs  
Chrome surround**

- Easiest to fit - No tools required
- Serrated plug and 3M tape
- 5 Year warranty



**Part Number**  
**37CCRM2P** - Multivolt 12-24V, Blister Single

**Function** Rear end outline marker  
**Size** 70mm x 35mm x 20mm  
**Voltage** Multivolt 12-24V  
**LED Qty** 2  
**Cable** 10cm with specially designed plugs

**Draw** @13.8V @28V  
0,04A 0,04A

**Approvals** **Function** **Category** **CRN**  
**ECE** Rear end 02R1 6917



**Part Number**  
**37CCAM2P** - Multivolt 12-24V, Blister Single

**Function** Side direction indicator  
**Size** 70mm x 35mm x 20mm  
**Voltage** Multivolt 12-24V  
**LED Qty** 2  
**Cable** 10cm with specially designed plug

**Draw** @13.8V @28V  
0,04A 0,04A

**Approvals** **Function** **Category** **CRN**  
**ECE** Indicator 00SM1 1017



**Part Number**  
**37CCARM2P** - Multivolt 12-24V, Blister Single

**Function** Red/Amber Side marker  
**Size** 70mm x 35mm x 20mm  
**Voltage** Multivolt 12-24V  
**LED Qty** 2  
**Cable** 10cm with specially designed plug

**Draw** @13.8V @28V  
0,04A 0,04A

**Approvals** **Function** **Category** **CRN**  
**ADR** Side 45/01 43515



**Part Number**  
**37CCWM2P** - Multivolt 12-24V, Blister Single

**Function** Front end outline marker  
**Size** 70mm x 35mm x 20mm  
**Voltage** Multivolt 12-24V  
**LED Qty** 2  
**Cable** 10cm with specially designed plug


**Draw** @13.8V @28V  
0,04A 0,04A

**Approvals** **Function** **Category** **CRN**  
**ECE** Front 02A 6918

**Fitting Instructions**

Drill two 6mm holes for serrated plugs and one 8mm hole or larger for the cable. Remove the protective film from the back and simply push into place. Please refer to ADR 13/00 for mounting instructions.

**Technical Drawings**



**Blister Packaging**

